

Outdoor/Indoor Light Control Instructions

SLC4CG, SLC4CW, SLC4CWL, SLC4CPL, SLC4CPLL

OUTDOOR USE: This Light Control will turn your patio lights or any outdoor light fixture "ON" and "OFF" automatically. (Outdoor use only in a raintight fixture.)

INDOOR USE: This Light Control can turn your light fixture "ON" and "OFF" during your absence to simulate home occupancy. The light fixture should be without a shade and placed so the Light Control photocell opening is facing a window less than 3 feet away.

This Light Control, when facing a good source of natural daylight, will turn "ON" at dusk and "OFF" at dawn. Frosted glass fixtures or adjacent light bulbs can cause slight blinking under certain light conditions. This problem can be overcome by rotating the photocell opening slightly or by using a lower wattage light bulb.

1. Unscrew bulb from light fixture. Screw light bulb into Light Control and screw unit, with attached light bulb into light fixture.
2. Rotate photocell opening to face a strong source of daylight, but away from any artificial or reflected light source.
3. Turn "ON" switch used to control lamp. The Light Control will turn your light "ON" at dusk and "OFF" at dawn automatically.
4. For daytime installation, covering the lens firmly with black tape should light the bulb. For night installation, shining a flashlight at the lens should turn the light off.

NOTE: When the Light Control switches "ON" at dusk and "OFF" at dawn the bulb may be partially bright or flicker slightly for some time. This is normal. To extend bulb life and increase energy savings, unit will decrease light output 20% to 25%. This Light Control is for use with incandescent bulbs only. Use 150 watts or less if bulb is installed pointing up or 100 watts or less if bulb is installed in a closed or poorly ventilated fixture. Do not use with any bug or insect light bulb. Bug and insect light bulbs create excessive heat. Do not use this control with another light control or dimmer in the same circuit.

1 Year Limited Warranty

AmerTac™ warrants this product to be free from defects in material and workmanship for a period of 1 year from the date of purchase. AmerTac's obligations are limited to repairing or replacing any defective units and are effective only if such units are returned within 1 year of the purchase date, to AmerTac, 250 Boulder Drive, Breinigsville, PA 18031. Warranty void if damage is due to accident, negligence, misuse, alteration or improper installation. In no circumstance will AmerTac be liable for consequential or incidental damages relating in any way to this product.

Questions, ¿Preguntas?, La question? 1-800-777-0802

©2009 AmerTac™
250 Boulder Drive
Breinigsville, PA 18031
www.amertac.com
Made in China / Hecho en China / Fabriqué en Chine
109-0051-A IN

Dry or Damp Locations Only
Incandescent / Halogen
120~V, 60HZ, 150 Watts Max

Certified to
CSA C22.2 No. 43-08

Conforms to
ULSTD 496



3095362