

10316 - GE garage & basement 30 watt T8 1-pack

F30T8/CW 6PK

- ☞ Ideal for utility use
- ☞ Lasts 3.4 years based on 6 hours per day usage
- ☞ 4100K cool white light appearance
- ☞ Cool white light perfect for sizable spaces
- ☞ For use in large spaces such as basements and garages
- ☞ GE garage & basement fluorescent bulbs' cool white light is perfect for illuminating sizable spaces throughout your home. Use in large open spaces in your home including finished and unfinished basements, garages and rec rooms
- ☞ 1.0 inch diameter T8 with medium bi-pin (g13) base
- ☞ 36 inches long

PRODUCT PHOTO



GENERAL CHARACTERISTICS

Base Description	Medium Bi-Pin
Base Type	Pin/Plug-In
Mercury Content	8 mg
Mercury-Picogram per mean lm hr	538.7
Starting Temp (MIN) C-degrees	10 °C
Bulb Material	Soda lime
Rated Life Hours-nominal	7500 h
Primary Application	Full Wattage
Product Technology	Linear Fluorescent
Base	G13
Bulb Shape	T8

PHOTOMETRIC CHARACTERISTICS

Mean Lumens nominal	1980 lm
Nominal Initial Lumen per Watt	72
Initial Lumens-nominal	2150 lm
Color Rendering Index-CRI	60
Color Temperature	4100 K

PRODUCT INFORMATION

Product Code	10316
Description	F30T8/CW 6PK
Alternative Unit Of Measure	CASE
Standard Package Quantity	6
Ean UPC	043168980524
Standard Package GTIN	00043168103169
No Of Items Per Sales Unit	
No Of Items Per Standard Package	6
Sales Unit	Case
UCC	043168103169
Alternative Unit Of Measure	EACH
Standard Package Quantity	1
Ean UPC	043168980524
Standard Package GTIN	00043168980524
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	1
Sales Unit	Each
UCC	043168103169

DIMENSIONS

Bulb Diameter (DIA) <Max>	1.1 in
Bulb Diameter (DIA) <Min>	0.94 in
Diameter	1.0 in
End of Base Pin to Pin	35.67 in
Face to End of Opposing Pin (B) <Max>	35.5 in
Face to End of Opposing Pin (B) <Min>	35.4 in
Nominal Length	36.0 in

ELECTRICAL CHARACTERISTICS

Current Crest Factor (MAX)	1.7
Cathode Resistance Ratio - Rh/Rc (MIN)	4.250
Cathode Resistance Ratio - Rh/Rc (MAX)	6.500
Rated power (Watts)	30 W

CAUTIONS & WARNINGS

Caution

- Lamp may shatter and cause injury if broken
- Wear safety glasses and gloves when handling lamp.
- Do not use excessive force when installing lamp.

Warning

- Risk of Electric Shock

Turn power off before inspection
installation or removal.

