

ELECTRONIC HID BALLASTS

Electronic HID Overview

Just as electronic ballast technology enhanced fluorescent lighting systems, electronic HID ballasts may bring significant performance improvements to HID lighting systems, including:

- Higher efficiency
- Greater lumen maintenance
- Longer lamp life
- Enhanced color control

e-Vision

Low frequency electronic ballasts are recommended by lamp manufacturers to drive the latest generation of ceramic, low wattage metal halide lamps. These ceramic lamps have superior color rendition and can potentially maintain that color over the life of the lamps when operated with electronic ballasts. Since color is dependent on proper lamp wattage, the electronic ballast must be able to maintain lamp wattage precisely at its rated point throughout the rated average life of the lamp. Low frequency electronic HID ballasts such as the Philips Advance e-Vision line constantly measure and adjust the wattage, optimizing delivery of the ceramic lamps' superior color properties. This makes ceramic metal halide operated by e-Vision ballasts the premier choice for many applications previously illuminated by either tungsten halogen or incandescent sources, such as retail lighting.

Operational improvements are gained as greater efficiency and cooler running electronic ballasts lead to energy savings. In addition, ballasts run quieter, weigh less and have compact footprints.

CosmoPolis

CosmoPolis presents a major step forward in outdoor lighting and was developed specifically to meet the challenges of the 21st century. The CosmoPolis system simplifies outdoor lighting with the combination of a compact lamp and an optimized, rugged electronic ballast system. Designed specifically for outdoor area and roadway lighting applications, these Xtreme ballasts have integral surge protection of 10kV/5kA, and 80,000 hours rated average life.* This highly efficient system provides end users the ability to convert to a warm white light without sacrificing color rendering or system lifetime.

CosmoPolis Programmable

The CosmoPolis Programmable Xtreme ballasts enable digitally based, networked control of CosmoPolis Systems. These ballasts use the DALI digital universal interface for control. The CosmoPolis Programmable System allows the end user maximum flexibility to control the lighting system. Features include:

1. Light sensor or switched supply control.
2. Constant or Adjustable Light Output.
3. Integrated line switch for pilot line or motion sensor control.
4. Line Voltage Dimming.
5. Integrated DynaDimmer allows user to program 5 different lighting levels and durations.
6. Network control and monitoring of each lamp and ballast on the system via powerline or RF using DALI based system such as Philips AmpLight & Starsense.
7. Software upgrades for system.

MasterColor Elite Medium Wattage

The lamp's sparkling white light with 90 CRI creates a natural ambiance and brings out the best in all different types of colors. The high efficiency of the lamp and ballast together means reduced energy use and a lower cost of ownership compared to traditional 400W Metal Halide HID systems.** The e-Vision ballast comes with 0-10V control wires that allow for dimming to 50% of lamp power and allow for operation by 0-10V controls such as the Philips DynaDimmer. This system is ideal for indoor lighting in both high-bay and recessed applications, as well as outdoor lighting for street and area installations. The MasterColor CDM Elite Xtreme ballast for 210W operation includes the same 10kV/5kA surge protection and 80,000 hour rated average life* as found in the CosmoPolis Xtreme ballasts.

* Rated average life is based on 90% surviving when operating at 10°C less than the marked maximum case temperature (T_c - 10°C) with one switch per day. Rated average life is based on engineering testing in laboratory conditions and probability data as defined in IEC Norm 60929.

** Based on a comparison of published data of a Philips CDM Elite MW 315/T9/942/U/E lamp operated by Philips Advance IZTMH-210315-R-LF (341 System Watts) to a Philips MS400/BU/ED28/PS operated by a Philips Advance 71A6092AEE ballast (452 system Watts) operated for 30,000 hours (rated average life of 315W CDM Elite lamp).

ELECTRONIC HID BALLASTS

Catalog Number Explanation

I	ZT	MH	—	100	A	BLS	ID															
<p>Additional Features: Blank = None ID = Integral 120V output to supply power to a 4-Wire Self Heating Thermal Protector (39W, 70W, 100W)</p>																						
<p>Lead Exit / Mounting Options: BLS = Bottom Leads with Studs LF = Leads (side exit) with mounting Feet LFS = Leads (side exit, lead exit from same end) with mounting Feet (K metal case models only) LS = Connector (side exit) with mounting Feet</p>																						
<p>Can Material / Size: (Dimensions include mounting feet)</p> <table border="0"> <tr> <td>A/B = Metal case with dim. 5.5" L x 3.6" W x 1.5" H</td> <td>K = Metal case with dim. 4.75" L x 1.3" W x 1.2" H</td> </tr> <tr> <td>D = Metal case with dim. 5.0" L x 3.0" W x 1.5" H</td> <td>M = Plastic case with dim. 5.9" L x 2.6" W x 2.6" H</td> </tr> <tr> <td>E = Metal case with dim. 5.5" L x 1.75" W x 1.2" H</td> <td>N = Plastic case with dim. 5.3" L x 2.6" W x 2.6" H</td> </tr> <tr> <td>G = Metal case with dim. 3.9" L x 3.0" W x 1.2" H</td> <td>Q = Plastic case with dim. 5.9" L x 3.5" W x 1.5" H</td> </tr> <tr> <td>H = Metal case with dim. 6.4" L x 3.7" W x 1.5" H</td> <td>R = Metal case with dim. 8.2" L x 4.9" W x 2.2" H</td> </tr> <tr> <td></td> <td>T = Plastic case with dim. 6.3" L x 3.9" W x 2.4" H</td> </tr> </table>								A/B = Metal case with dim. 5.5" L x 3.6" W x 1.5" H	K = Metal case with dim. 4.75" L x 1.3" W x 1.2" H	D = Metal case with dim. 5.0" L x 3.0" W x 1.5" H	M = Plastic case with dim. 5.9" L x 2.6" W x 2.6" H	E = Metal case with dim. 5.5" L x 1.75" W x 1.2" H	N = Plastic case with dim. 5.3" L x 2.6" W x 2.6" H	G = Metal case with dim. 3.9" L x 3.0" W x 1.2" H	Q = Plastic case with dim. 5.9" L x 3.5" W x 1.5" H	H = Metal case with dim. 6.4" L x 3.7" W x 1.5" H	R = Metal case with dim. 8.2" L x 4.9" W x 2.2" H		T = Plastic case with dim. 6.3" L x 3.9" W x 2.4" H			
A/B = Metal case with dim. 5.5" L x 3.6" W x 1.5" H	K = Metal case with dim. 4.75" L x 1.3" W x 1.2" H																					
D = Metal case with dim. 5.0" L x 3.0" W x 1.5" H	M = Plastic case with dim. 5.9" L x 2.6" W x 2.6" H																					
E = Metal case with dim. 5.5" L x 1.75" W x 1.2" H	N = Plastic case with dim. 5.3" L x 2.6" W x 2.6" H																					
G = Metal case with dim. 3.9" L x 3.0" W x 1.2" H	Q = Plastic case with dim. 5.9" L x 3.5" W x 1.5" H																					
H = Metal case with dim. 6.4" L x 3.7" W x 1.5" H	R = Metal case with dim. 8.2" L x 4.9" W x 2.2" H																					
	T = Plastic case with dim. 6.3" L x 3.9" W x 2.4" H																					
<p>Max Lamp Wattage:</p> <table border="0"> <tr> <td>G20 = 20W Lamp, ANSI C156/M156</td> <td>P39 = 39W Lamp+</td> <td>60 = 60W Lamp</td> <td>100 = 100W Lamp</td> <td>210315 = 210W or 315W Lamp</td> </tr> <tr> <td>20 = 22 W Lamp^</td> <td>45 = 45W Lamp</td> <td>70 = 70W Lamp</td> <td>140 = 140W Lamp</td> <td>210 = 210W Lamp</td> </tr> <tr> <td>39 = 39 W Lamp, ANSI C130/M130</td> <td>50 = 50W Lamp</td> <td>90 = 90W Lamp</td> <td>150 = 150W Lamp</td> <td></td> </tr> </table>								G20 = 20W Lamp, ANSI C156/M156	P39 = 39W Lamp+	60 = 60W Lamp	100 = 100W Lamp	210315 = 210W or 315W Lamp	20 = 22 W Lamp^	45 = 45W Lamp	70 = 70W Lamp	140 = 140W Lamp	210 = 210W Lamp	39 = 39 W Lamp, ANSI C130/M130	50 = 50W Lamp	90 = 90W Lamp	150 = 150W Lamp	
G20 = 20W Lamp, ANSI C156/M156	P39 = 39W Lamp+	60 = 60W Lamp	100 = 100W Lamp	210315 = 210W or 315W Lamp																		
20 = 22 W Lamp^	45 = 45W Lamp	70 = 70W Lamp	140 = 140W Lamp	210 = 210W Lamp																		
39 = 39 W Lamp, ANSI C130/M130	50 = 50W Lamp	90 = 90W Lamp	150 = 150W Lamp																			
<p>Number of Lamps: Blank = 1 Lamp Operation 2 = (2) Lamp Operation</p>																						
<p>Primary Lamp Type: MH = Metal Halide CW = CosmoPolis Metal Halide</p>																						
<p>Dimming Scheme: Blank = Fixed Light Output ZT = 0-10V Dimming D = Programmable DALI Interface</p>																						
<p>Input Voltage: I = Intellivolt (accepts input of 120 thru 277V, 50/60 Hz nominal)‡ R = 120V, 50/60 Hz nominal</p>																						

^ Philips 22W MiniMaster Color Lamp, ANSI C175/M175, with PGJ5 base

+ Philips 39W MiniMaster Color Lamp, ANSI C179/M179, with PGJ5 base

‡ For CosmoPolis and MasterColor CDM Elite Medium Wattage, Intellivolt is limited to 208 thru 277V

ELECTRONIC HID BALLASTS

e-Vision Low Frequency Electronic HID Ballasts

For Low Wattage HID Lamps

Key Features	Key Benefits
IntelliVolt <ul style="list-style-type: none"> Operates on either 120 or 277V, or any voltage in between, 50 or 60Hz 	<ul style="list-style-type: none"> Fewer SKUs required in inventory Broadens the range of applications
Smaller and lighter weight than magnetic HID F-Can ballasts	<ul style="list-style-type: none"> Compact electronic HID footprints Provides greater design flexibility
Reduced input watts compared to magnetic systems	<ul style="list-style-type: none"> Energy Savings; Lower cost of ownership
Low frequency lamp operation	<ul style="list-style-type: none"> Prevents acoustic resonance in the lamp arc tube Recommended by lamp manufacturers
Square wave output waveform	<ul style="list-style-type: none"> Helps maximize lamp life
Lamp EOL detection; Shuts down system at lamp end of life	<ul style="list-style-type: none"> Enhanced safeguard
Thermally protected, internally fused, and output short circuit protected	<ul style="list-style-type: none"> Shuts system down upon abnormal failure or conditions
Lamp Wattage Regulation <ul style="list-style-type: none"> Lamp wattage will change less than .5% with a +/-10% change in line voltage 	Excellent light quality <ul style="list-style-type: none"> Optimizes lamp color stability over rated average life Reduces lamp-to-lamp color variations both initially and during lamp life
Metallic enclosure	<ul style="list-style-type: none"> Provides enhanced capability for high ambient temperatures by transferring heat away from sensitive internal components
1.0 Ballast Factor	<ul style="list-style-type: none"> Lamp produces maximum light output over its rated average life

eHID Lead Wire Information

Wire Color	Function	Lengths Lead (-LF model)	Lengths (-BLS model)	Length Strip
Black	Input Power	11.0" +/- 1.0"	9.0" +3.0"/-2.0"	0.5"
White	Input Power	11.0" +/- 1.0"	9.0" +3.0"/-2.0"	0.5"
Red	Lamp Base	11.0" +/- 1.0"	9.0" +3.0"/-2.0"	0.5"
Blue	Lamp Screwshell	11.0" +/- 1.0"	9.0" +3.0"/-2.0"	0.5"
Green	Ground	11.0" +/- 1.0"	9.0" +3.0"/-2.0"	0.5"
Orange	Lamp Base (Second Lamp On 2-Lamp Ballasts)	11.0" +/- 1.0"	9.0" +3.0"/-2.0"	0.5"
Brown	Lamp Screwshell (Second Lamp On 2-Lamp Ballasts)	11.0" +/- 1.0"	9.0" +3.0"/-2.0"	0.5"
Yellow	Output for 120V Self Heating Thermal protector	N/A	9.0" +3.0"/-2.0"	0.5"
Gray with Red Stripe	Output for 120V Self Heating Thermal protector	N/A	9.0" +3.0"/-2.0"	0.5"

Metal Halide

Lamp Data		Input Volts	Catalog Number* <i>Note 1</i>	Certifications				Line Current (Amps)	Input Power ANSI (Watts)	Max. Case Temp. <i>Note 3</i>	Wiring Diag.	Fig.	Weight (lb)	Max. Distance to Lamp (ft)
Number	Watts			E	UL	SF	RoHS COMPLIANT							
50W Lamp, ANSI Code M110, or C193(Philips CDM Elite), Minimum Starting Temp. -20°C/-4°F														
I	50	120	IMH-50-E-LF	✓	✓	✓	0.48	57	90°C	3	E	0.8	5	
		277					0.20	56						
I	50	120	IMH-50-K-LF, IMH-50-K-BLS or IMH-50-K-LFS <i>Note 2</i>	✓	✓	✓	0.48	57	90°C	3	K	0.5	4	
		277					0.21	56						
I	50	120	IMH-50-G-LF or IMH-50-G-BLS	✓	✓	✓	0.47	56	90°C	3	G	0.9	3	
		277					0.21	55						
70W Lamp, ANSI Code M98/C98 or M139/C139 or M143, Minimum Starting Temp. -20°C/-4°F														
I	70	120	IMH-70-G-LF or IMH-70-G-BLS	✓	✓	✓	0.66	79	90°C	3	G	0.9	3	
		277					0.28	76						
I	70	120	IMH-70-E-LF	✓	✓	✓	0.68	80	90°C	3	E	0.8	5	
		277					0.29	78						
I	70	120	IMH-70-D-LF or IMH-70-D-BLS	✓	✓	✓	0.66	79	85°C	3	D	1.6	3	
		277					0.28	76						
I	70	120	IMH-70-A-BLS-ID*	✓	✓	✓	0.72	86	90°C	8	A	1.6	6	
		277					0.31	84						
100W Lamp, ANSI Code M90/C90 or M140 or C191, Minimum Starting Temp. -20°C/-4°F														
I	100	120	IMH-100-D-LF or IMH-100-D-BLS	✓	✓	✓	0.92	110	85°C	3	D	1.6	5	
		277					0.40	109						
I	100	120	IMH-100-B-LF	✓	✓	✓	0.92	110	85°C	3	B	1.5	5	
		277					0.40	109						
I	100	120	IMH-100-A-BLS-ID*	✓	✓	✓	0.96	115	90°C	8	A	1.4	6	
		277					0.42	113						
150W Lamp, ANSI Code M102/C102 or M142/C142, Minimum Starting Temp. -20°C/-4°F														
I	150	120	IMH-150-H-LF or IMH-150-H-BLS <i>Note 4</i>	✓	✓	✓	✓	1.4	165	85°C	3	H	1.9	5
		277						0.6	161					

- All ballasts are sound rated A, and feature high power factor (>0.9, a ballast factor of 1.0 resettable thermal protection, and a maximum Harmonic Distortion of 15%.
- For IMH-39-K-LF, RMH-39-K-LF, RMH-20-K-LF and IMH-G20-K-LF input and output lead wires exit on opposite sides of ballast. For IMH-39-K-LFS, RMH-39-K-LFS, RMH-20-K-LFS and IMH-G20-K-LFS all lead wires exit the same side of the ballast.
- Maximum case temperature should not be exceeded in the application, as life will be affected and the integral re-settable thermal protector may activate. A lower maximum temperature rating does not imply lesser thermal performance, and can be indicative of a cooler running ballast design. Consult factory for further application assistance.
- "Circle E" denotes EISA compliance

* Ordering information:

- LF Side exit leads with mounting feet
- BLS Bottom exit leads with mounting studs

✕ Use with any Self Heating Thermal Protector (Insulation Detector) having equivalent resistive value 5k to 25k ohm (4 wire versions only)

¥ Restrictions on Hazardous Substances (RoHS) is a European directive (2002/95/EC) designed to limit the content of 6 substances [lead, mercury, cadmium, hexavalent chromium, polybrominated biphenyls (PBB), and polybrominated diphenyl ethers (PBDE)] in electrical and electronic products

Refer to page 6-3 for lead wire information

Refer to pages 6-10 to 6-11 for ballast dimensions