



Optanium T8 Instant Start

OPTANIUM ELE BALLAST (2) F96T8 120-277V

Reliable and energy efficient Philips Advance's Centium commercial grade specifications, plus added benefits of lamp striation reduction technology.

Product data

General Information Lamp Type F96T8 Number of Lamps 1/2 piece/unit Ballast Type Electronic Fluorescent Base Model IOP2P59N Suitable For Outdoor Use Yes Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Max THD 10 % Starting Method Instant Start Lamp Current Crest Factor (Nom) 1.6 Ignition Time (Nom) 0.1 s Ballast Factor (Nom) 0.98 Input Current (Operating) (Max) 0.95 A Input Current (Operating) (Min) 0.4 A		
Number of Lamps 1/2 piece/unit Ballast Type Electronic Fluorescent Base Model IOP2P59N Suitable For Outdoor Use Yes Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Max THD 10 % Starting Method Instant Start Lamp Current Crest Factor (Nom) 1.6 Ignition Time (Nom) 0.1 s Ballast Factor (Nom) 0.98 Input Current (Operating) (Max) 0.95 A	General Information	
Ballast Type Electronic Fluorescent Base Model IOP2P59N Suitable For Outdoor Use Yes Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Max THD 10 % Starting Method Instant Start Lamp Current Crest Factor (Nom) 1.6 Ignition Time (Nom) 0.1 s Ballast Factor (Nom) 0.98 Input Current (Operating) (Max) 0.95 A	Lamp Type	F96T8
Base Model IOP2P59N Suitable For Outdoor Use Yes Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Max THD 10 % Starting Method Instant Start Lamp Current Crest Factor (Nom) 1.6 Ignition Time (Nom) 0.1 s Ballast Factor (Nom) 0.87 Power Factor (Nom) 0.98 Input Current (Operating) (Max) 0.95 A	Number of Lamps	1/2 piece/unit
Suitable For Outdoor Use Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Max THD 10 % Starting Method Instant Start Lamp Current Crest Factor (Nom) 1.6 Ignition Time (Nom) 0.1 s Ballast Factor (Nom) 0.87 Power Factor (Nom) 0.98 Input Current (Operating) (Max) 0.95 A	Ballast Type	Electronic Fluorescent
Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Max THD 10 % Starting Method Instant Start Lamp Current Crest Factor (Nom) 1.6 Ignition Time (Nom) 0.1 s Ballast Factor (Nom) 0.87 Power Factor (Nom) 0.98 Input Current (Operating) (Max) 0.95 A	Base Model	IOP2P59N
Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Max THD 10 % Starting Method Instant Start Lamp Current Crest Factor (Nom) 1.6 Ignition Time (Nom) 0.1 s Ballast Factor (Nom) 0.87 Power Factor (Nom) 0.98 Input Current (Operating) (Max) 0.95 A	Suitable For Outdoor Use	Yes
Input Voltage	Automatic Restart	Yes
Input Voltage		
Input Frequency	Operating and Electrical	
Max THD 10 % Starting Method Instant Start Lamp Current Crest Factor (Nom) 1.6 Ignition Time (Nom) 0.1 s Ballast Factor (Nom) 0.87 Power Factor (Nom) 0.98 Input Current (Operating) (Max) 0.95 A	Input Voltage	120 to 277 V
Starting Method Instant Start Lamp Current Crest Factor (Nom) 1.6 Ignition Time (Nom) 0.1 s Ballast Factor (Nom) 0.87 Power Factor (Nom) 0.98 Input Current (Operating) (Max) 0.95 A	Input Frequency	50 to 60 Hz
Lamp Current Crest Factor (Nom) 1.6 Ignition Time (Nom) 0.1 s Ballast Factor (Nom) 0.87 Power Factor (Nom) 0.98 Input Current (Operating) (Max) 0.95 A	Max THD	10 %
Ignition Time (Nom)	Starting Method	Instant Start
Ballast Factor (Nom) 0.87 Power Factor (Nom) 0.98 Input Current (Operating) (Max) 0.95 A	Lamp Current Crest Factor (Nom)	1.6
Power Factor (Nom) 0.98 Input Current (Operating) (Max) 0.95 A	Ignition Time (Nom)	0.1 s
Input Current (Operating) (Max) 0.95 A	Ballast Factor (Nom)	0.87
	Power Factor (Nom)	0.98
Input Current (Operating) (Min) 0.4 A	Input Current (Operating) (Max)	0.95 A
	Input Current (Operating) (Min)	0.4 A
Input Power (Nom) 113-111 W	Input Power (Nom)	113-111 W
Rated Lamp Watts 59 W	Rated Lamp Watts	59 W

Wiring	
Color Input Terminals	No terminals
Color Output Terminals	No terminals
Wire Striplength	0.50/0.375 mm
Lamp Connection	Parallel
Wire Length by Color	See data sheet
Wire Gauge (Nom)	18AWG mm
Wire Type	Solid
Remote Wiring Configuration Allowed	Yes
Tandem Wiring Configuration Allowed	Yes
Through Wiring Configuration Allowed	Yes
Max Ballast-Lamp Distance Remote Wiring	20'
Max Ballast-Lamp Distance Tandem Wiring	Any = 20'
Max Ballast-Lamp Distance Through Wiring	Any = 20'
Connector Type	No connector
Temperature	
T-Case Maximum (Nom)	70 °C
Mechanical and Housing	
Housing Material	Metal
Housing	N


Datasheet, 2016, February 1 data subject to change

Optanium T8 Instant Start

Housing Dimensions	9.5" x 1.3" x 1.0"
Approval and Application	
EMC Immunity Standard	FCC Non-Consumer
Approbation Marks	CSA certificate UL certificate CEC Listing Circle E
	logo DOE RoHS Compliant
Sound Rating	A
UL Recognized	No
Product Data	
Order product name	OPTANIUM IOP2P59N35M

EAN/UPC - Product	781087135631
Order code	IOP2P59N35M
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	30
Material Nr. (12NC)	913701262102
Net Weight (Piece)	350.000 g

Dimensional drawing



ELE BALLAST (2) F96T8 120-277V

