
# **Buildex**

## **E-Z Ancor**<sup>®</sup> Self-Drilling Drywall Anchors

The Original, Fast and easy self-drilling anchors. E-Z Zinc™,

E-Z Stud Solver™, E-Z Mini™, E-Z Lite™, E-Z Plastic Plus™,

Twist-N-Lock<sup>™</sup>, and E-Z Toggle<sup>™</sup>



#### Applications Electrical Fixtures Plagues and Awards Smoke Detectors Thermostats **Closet Organizers** Clocks **HVAC Fixtures** Coat Racks **Kitchen Accessories Plumbing Fixtures** Curtain Rods Doorbells **Bathroom Accessories Telecommunications Equipment** Signs Shelving and Supports **Bulletin Boards** Chalk Boards **Remote Control Boxes** Mirrors **Control Systems Picture Frames Decorative Wall Hangings** Brackets Office Material Holders . . . . . . . . . . . Product Features No hole preparation necessary; pre-drills own Available in corrosion resistant, non-conductive small precise hole in gypsum wallboard. white nylon. Replaces plastic plugs and toggles. Can be easily backed-out. Deep thread design provides strong engagement Low profile head. in 3/8", 1/2" and 5/8" gypsum wallboard. Single point designs for clean cutting installation. Installs quickly and easily with a phillips screwdriver or square drive bit. Stud Solver - attachments through gypsum and wood! Works in double drywall applications, too! - #8 diameter 1-1/4" screws included Full range of anchors to cover all wall fastening applications. - Bulk packaging only

### **Product Specifications**

## **E-Z PRODUCTS** Self-Drilling Drywall Anchors Selector Guide

		Anchor Description	Anchor Material	Part Number	Quantity	Maximum Fixture Thickness	Accommodates Sheet Metal Screw Size
Light Duty	E-Z Lite		White Nylon	5006902 5006900	10 – 100 ct boxes Bulk - 10,000 Anchors	3/4"	#6
	E-Z Mini		Zinc	5033902 5033900	10 – 100 ct boxes Bulk - 3,000 Anchors	3/4''	#6, #7
Medium Duty	Stud Solver"		Zinc	5052900	Bulk Only - 1,500 Anchors & Screws	3/4''	Use only with #8 screw provided
	E-Z Zinc <sup></sup>		Zinc	5000902 5000900	10 – 100 ct boxes Bulk - 1,500 Anchors	3/4''	#6, #7, or #8
	E-Z Plastic Plus <sup></sup>		White Nylon	5035902 5035900	10 – 100 ct boxes Bulk - 4,500 Anchors	3/4"	#6, #7, or #8
	Twist-N- Lock"		White Nylon	5061902 5061900	10 – 100 ct boxes Bulk - 4,500 Anchors	3/4"	Refer to sizes on back inside cover
Heavy Duty	oggle		Zinc	5014901 5014900	50 ct – 50 #8 x 2-1/8" Pan SMS Bulk - 500 Anchors & Screws	1/2"	#8
	E-Z T(			5017901 5017900	50 ct – 50 #8 x 2-1/8" Large Washer Face SMS Bulk - 500 Anchors & Screws		


### **Performance Data**

These performance values are averages obtained under laboratory conditions. Note that these values will change depending on age, moisture content and surface treatment of the drywall (gypsum) material. Appropriate safety factors should be applied to these values for design purposes.

	ULTIMATE HOLDING WEIGHT				
DRYWALL THICKNESS	3/8"	1/2"	5/8"		
Light Duty Plastic	25 lbs.	30 lbs.	40 lbs.		
Light Duty Zinc	30 lbs.	40 lbs.	50 lbs.		
Medium Duty	40 lbs.	50 lbs.	75 lbs.		
Twist-N-Lock	65 lbs.	75 lbs.	80 lbs.		
Heavy Duty	70 lbs.	85 lbs.	150 lbs.		

### **Installation Guidelines**

### Light Duty & Medium Duty E-Z Ancors




Place #2 Phillips screwdriver into recess of E-Z Zinc, E-Z Lite, E-Z Mini, E-Z Stud Solver, Twist-N-Lock, or E- Z Plastic Plus.

2. Press into drywall while turning the anchor clockwise until it is seated flush with wall.

Place fixture in position over installed E-Z Zinc, E-Z Lite, E-Z Mini , E-Z Stud Solver, Twist-N-Lock, or Plastic Plus. Insert screw with screw driver. Tighten fixture in

### Heavy Duty E-Z Toggle



1. Using a #2 Phillips screwdriver, screw the E-Z Toggle Anchor into drywall until the head of the anchor is seated flush.

2. To "set" the clamp behind the drywall, place the mounting scrw into the anchor and push or tap firmly until approximately 1" of screw is protruding (do not rotate). Then remove the screw.

3. Place fixture over E-Z Toggle, insert screw and continue to turn until fastened tightly (for example when attaching a 1/2" thick fixture, it will require approx. 23 full rotations of the screwdriver to fully tighten the fixture).

\* Do Not Use For Mounting Televisions \*

