

TO BE INSTALLED AND/OR USED IN ACCORDANCE WITH
APPROPRIATE ELECTRICAL CODES AND REGULATIONS

3-Way Grounding Switch
Rated: 15A-120VAC

TO INSTALL:

WARNING: TO AVOID FIRE, SHOCK, OR DEATH; TURN
OFF POWER AT CIRCUIT BREAKER OR FUSE AND TEST
THAT THE POWER IS OFF BEFORE WIRING!

CAUTION: USE THIS DEVICE ONLY WITH COPPER OR
COPPER CLAD WIRE. WITH ALUMINUM WIRE USE ONLY
DEVICES MARKED CO/ALR OR CU/AL.

Remove insulation per strip gage on device (about 5/8").

Connect wires per WIRING DIAGRAM as follows:

To Side Wire:

Loop wires clockwise 3/4 turn around terminal screws.
Firmly tighten screws over wire loops. Terminal screws
accept up to #12 AWG copper or copper clad wire.

To Quickwire™:

Insert straight #14 AWG solid copper wires into round
Quickwire™ holes. If the switch must be replaced or
rewired after Quickwiring, gently press the tip of a small
screwdriver in the release slot and back the wire out
gradually. If the switch or Quickwire™ terminal become
damaged, do not reuse.

Mount device using long mounting screws.

Attach wallplate. Restore power at circuit breaker or fuse.

Installation is complete.

