

# 8 Ft. 40W (59W Replacement) Cool White (4000K) FA8 Base (T8 & T12 Replacement) Ballast Bypass (Type B) LED Linear Tube (2-Pack)

## Features

- Converts your existing fluorescent fixture to LED technology
- Ballast bypass installation requires direct wiring for longer installation time, but more efficient operation and less maintenance over time
- Shatter-proof lens and mercury-free, no special disposal is required



## Specifications

<b>Item Number</b>	<b>Item Width (In)</b>	<b>Item Length (In)</b>	<b>Bulb Shape</b>
T96/840/B/LEDG2/2	1.1	39.4	T8
<b>Bulb Type</b>	<b>Bulb Base</b>	<b>Bulb Finish</b>	<b>Dimmable</b>
Tubular	FA8	White	NO
<b>Technology</b>	<b>Energy Used (Wattage)</b>	<b>Replacement</b>	<b>Voltage</b>
LED - SMD	40	59	120-277
<b>Energy Efficiency</b>	<b>Annual Energy Cost</b>	<b>Brightness (LUMENS)</b>	<b>Lumen Efficiency (LPW)</b>
32.2%	4.82	5000	125.0
<b>Color Temperature (CCT)</b>	<b>Color Accuracy (CRI)</b>	<b>Life Years</b>	<b>Life Hours</b>
4000	80	32.0	35000
<b>Pack Quantity</b>	<b>CEC Compliant</b>	<b>Portable</b>	<b>Hardwire</b>
2	Not Regulated	NO	NO
<b>Battery Operated</b>	<b>Smart</b>	<b>Safety Location</b>	
NO	No	Damp	