## Grounding Kit



A Pentair Company

Ground Wire (Not Included)

Drill 7/32 inch diameter hole.

Bottom End of Enclosure

Ground Label

Hoffman Enclosures Inc. 2100 Hoffman Way. Anoka, MN 55303-1745 (763) 422-2211 Tel www.hoffmanonline.com

NOTE: Only use this ground kit where the use of this component is specified.

10-32x1 Screw

P/N 79208001

- 1. Drill 7/32 inch diameter hole in the bottom end of enclosure.
- 2. Remove paint where the ground connector will contact the enclosure to insure electrical continuity.
- 3. Install the ground connector and connect ground wire as shown.
- 4. Attach ground label adjacent to connector as shown.
- 5. If this enclosure has provisions for installing a panel, install the lockwasher included in the enclosure under one of the screws securing the panel. This will insure grounding between the panel and the enclosure.