



Reflector BR38 Flood

100PAR/1/R 120V 6/1 PK

Philips Family of Specialty Incandescents provide the perfect light for dramatic accents and display lighting as well as general lighting in a variety of applications. These reflector lamps come in multiple colors ideal for holiday, party or special effects lighting.

Product data

| General Information | |
|--------------------------|--|
| Cap-Base | E26 [Single Contact Medium Screw] |
| Bulb Shape | BR-38 |
| Operating Position | UNIVERSAL [Any or Universal (U)] |
| Gas Filling | Gas |
| Footnote Incandescent 1 | Circle E-The encircled E means this bulb meets Federal |
| | minimum efficiency standards. |
| | |
| Light Technical | |
| Beam Description | Flood |
| | |
| Operating and Electrical | |
| Power (Rated) (Nom) | 100 W |
| Voltage (Nom) | 120 V |
| | |

| Mechanical and Housing | | |
|-----------------------------------|------------------------|--|
| Bulb Finish | Red | |
| Cap-Base Information | Brass Cap | |
| Filament Shape | CC6 [Straight] | |
| | | |
| Product Data | | |
| Order product name | 100PAR/1/R 120V 6/1 PK | |
| EAN/UPC - Product | 046677285098 | |
| Order code | 925248336307 | |
| Numerator - Quantity Per Pack | 1 | |
| Numerator - Packs per outer box 6 | | |
| Material Nr. (12NC) | 925248336307 | |
| Net Weight (Piece) | 0.001 kg | |
| | | |


Datasheet, 2016, October 11 data subject to change

Reflector BR38 Flood

Dimensional drawing

Product

100PAR/1/R 120V 6/1 PK



100W E26 120V BR38 Red

